

LEDUC LED

120V Under Cabinet Lighting

Nora Lighting is proud to introduce LEDUC Series of 120V Dimmable Under Cabinet LED lighting. The LEDUC allows for easy retrofitting of existing Fluorescent, Incandescent, Halogen, or Xenon undercabinet lights. LEDUC's built in LED driver and large knockout plate in the back makes LEDUC easy to install in retrofit or new construction applications. A heavily frosted lens diffuses the LED image and softens the light output. Available in five sizes, two finishes, and warm 3000K or cool 4000K the new LEDUC LED Undercabinet is a designers choice for quality, energy efficient LED lighting.



FEATURES

- 120V Dimmable
- 250 Lumens / 4W per foot
- Self contained driver in each unit
- 3000K (Warm) and 4000K (Cool) color temperature
- 80+ CRI
- Osram® LEDs
- Frosted lens
- Bronze or White finishes
- Less than 1" in depth
- Each unit can be hardwired with Romex™ feed
- Each unit includes Romex™ connector
- Easy to mount with captive screws
- Linkable up to 400 Watts
- Each Unit includes End-to-End Connector



LEDUC LED UNDER CABINET LIGHT

CATALOG. NO.	LENGTH	WATTAGE	COLOR TEMP.	FINISH
NUD-7708/(temp)(finish)	8"	2.8W	3000K, 4000K	Bronze, White
NUD-7712/(temp)(finish)	12"	4W	3000K, 4000K	Bronze, White
NUD-7718/(temp)(finish)	18"	6W	3000K, 4000K	Bronze, White
NUD-7724/(temp)(finish)	24"	8W	3000K, 4000K	Bronze, White
NUD-7732/(temp)(finish)	32"	10W	3000K, 4000K	Bronze, White

Color Temps: **30** - 3000K, **40** - 4000K Finishes: **BZ** - Bronze, **W** - White

Example: NUD-7712/30W - 12" Warm 30K White finish Undercabinet



Illuminating the future...since 1989

TEL. 800.686.6672 | FAX 800.500.9955 | WWW.NORALIGHTING.COM

LED SPECIALTY

LEDUC LED Under Cabinet Accessories



NUD Series J-Box

NUA-402 BZ or W

Hardwire box used to power NUD Series using Jumper Cables or NUA-404 Hard wire connector. Includes on/off switch. L: 6-1/4" W: 3-5/8" H: 1"



NUD Series 72" Cord & Plug

NUA-405 B or W

Converts NUD Series LED fixtures from hardwire to direct plug-in units using connector pins on end of NUD unit. Grounded plug.



NUD Series End to End Connector

NUA-403 B or W


Used to seamlessly join two NUD LED fixtures. 3-Wire grounded connector. One included with each LEDUC unit



UD Series Jumper Cable

NUA-406	6"	B or W
NUA-412	12"	B or W
NUA-424	24"	B or W
NUA-472	72"	B or W

Used to join NUD Series LED fixtures together or to an NUA-402 J-box. 3-wire grounded cables.



NUD Series Hardwire Connector

NUA-404 B or W

3-Wire grounded connector/cable used to hardwire NUD Series LED fixture to NUA-402 or J-Box.

SAMPLE LAYOUT

